## Motorized drapery blinds system FLA-CL750



- •Motorized drapery system for both straight and curve curtains.
- \*Quiet dc motor, wireless remote control or dry contact control.
- •Track with self-lubricating design, with durable textile belt system, easy for insatallation.
- Intelligent electronic limit, resistance and stop function that can be extent the usage life both drives and track.
- With slow start, slow stop function.
- •Reserved TX RX GND interface, it can use your WIFI, Zigbee, Z-wave module.
- \*Touch control function can be switched on and off.
- \*Built-in radio receiver insideand dry contact control funtion.

•Customized RS485 control interface.convenient to apply with intelligent household control system

\*WIFI models support mobile APP control, and it can works with amazon Alexa Google assistant, and TMJL.

Curtain Motor Size: 300\*50\*60mm









ZigBee











Rs485 port or Dry contact

Program button indicate light

Drapery blinds system drive motor

Rated current Rated torque Rated speed Running time IP grade 2A FLA-CL750 100-240VAC 50/60Hz 115-138rpm S3 50% IP41 15Nm 0.16m/S

## Motorized drapery blinds system FLA-CL121



- Motorized drapery system for both straight and curve curtains.
- •Quiet dc motor, wireless remote control or dry contact control.
- •Track with self-lubricating design, with durable textile belt system, easy for insatallation. •Intelligent electronic limit, resistance and stop function that can be extent the usage life both drives and track.
- · With slow start, slow stop function.
- Reserved TX RX GND interface, it can use your WIFI, Zigbee, Z-wave module.
- Touch control function can be switched on and off.
- •Built-in radio receiver inside and dry contact control funtion.
- •Built-in radio receiver inside, which is compatible with all YGHOCStransmitters.
- •Customized RS485 control interface.convenient to apply with intelligent household control system
- •WIFI models support mobile APP control, and it can works with amazon Alexa Google assistant, and TMJL.
- •Can make USA, Australian, European z-wave frequency compatible all z-wave







Curtain Motor Size: 327\*50.6\*60mm





**WAVE** 














Drapery blinds system Headpart of

Product model	Rated voltage	Rated frequency	Rated current	Rated torque	Rated speed	Speed	Running time	IP grade
FLA-CL121	100-240VAC	50/60Hz	2A	2Nm	112rpm	0.16m/S	S3 50%	IP41